NASA TECHNICAL NOTE



NASA TN D-6709

LOAN COPY: RETURE AFWL (DOUL)

DESIGN OF RECURSIVE DIGITAL FILTERS HAVING SPECIFIED PHASE AND MAGNITUDE CHARACTERISTICS

by

Robert E. King

Langley Research Center

and

Gregory W. Condon

Langley Directorate,

U.S. Army Air Mobility R&D Laboratory



NATIONAL AERONAUTICS AND SPACE ADMINISTRATION - WASHINGTON, D. C. - APRIL 1972

1. Report No. NASA TN D-6709 2. Government A A Title and Subtitle DESIGN OF RECURSIVE DIGITAL FILTER SPECIFIED PHASE AND MAGNITUDE CHA	Accession No.	3. Recipient's Catalog	133397 No.
4. Title and Subtitle DESIGN OF RECURSIVE DIGITAL FILTER			
		5. Report Date	
SPECIFIED PHASE AND MAGNITUDE CHA	S HAVING	April 1972	
	ARACTERISTICS	6. Performing Organiza	ation Code
7. Author(s)	·-	8. Performing Organiza	tion Report No.
Robert E. King; and Gregory W. Condon, L		L-8162	
U.S. Army Air Mobil	ity R&D Laboratory	10. Work Unit No.	
9. Performing Organization Name and Address	1.	760-72-03-0	01
NASA Langley Research Center		Contract or Grant I	No.
Hampton, Va. 23365			
<u>-</u>		13. Type of Report and	d Period Covered
12. Sponsoring Agency Name and Address		Technical N	Tote
National Aeronautics and Space Administration Washington, D.C. 20546	ation	14. Sponsoring Agency	Code
15. Supplementary Notes			
tions in the frequency domain of both magnextension to the work of Steiglitz, uses the squared magnitude and phase criterion. Favoring specified phase as well as specified	Fletcher-Powell algoritesults using the algorit	ithm to minimize hm for the desig	e a weighted on of filters
17. Key Words (Suggested by Author(s)) Digital filter Computer-aided design Phase specification	18. Distribution Statement Unclassified		
Digital filter Computer-aided design Phase specification			22. Price*

DESIGN OF RECURSIVE DIGITAL FILTERS HAVING SPECIFIED PHASE AND MAGNITUDE CHARACTERISTICS

By Robert E. King Langley Research Center

and

Gregory W. Condon
Langley Directorate, U.S. Army Air Mobility R&D Laboratory

SUMMARY

A method for a computer-aided design of a class of optimum filters, having specifications in the frequency domain of both magnitude and phase, is described. The method, an extension to the work of Steiglitz, uses the Fletcher-Powell algorithm to minimize a weighted squared magnitude and phase criterion. Results using the algorithm for the design of filters having specified phase as well as specified magnitude and phase compromise are presented.

INTRODUCTION

Recursive filters, wherein the output sequence is both a function of the input as well as past output samples, are commonly used in digital signal processing and analysis. Such digital filters in many applications offer distinct advantages of precision and versatility over their continuous or analog counterparts. There exist a number of design procedures for implementing digital filters (see ref. 1) each one of which strives to attain some analogy between discrete and continuous systems. Transform methods such as the matched-z, bilinear-z, and standard-z which lead to specific property invariances are available (see ref. 2) to the designer familiar with continuous filter design.

For frequency-domain synthesis (see refs. 3 and 4), realization is normally by means of cascade or parallel combinations of pole and zero pairs in the complex plane. The synthesis problem is, in fact, reduced to one of approximation since the filter topology is generally specified. In none of the available design procedures, which can yield filters having excellent magnitude-frequency characteristics, however, do the resultant filters, in themselves, have particularly useful phase characteristics. Indeed, in striving for particular magnitude characteristics by using any of the available design methods, there is no control over the filter phase properties.

In practice, it is often desirable to specify a digital filter in the frequency domain by its phase (see ref. 5) or even a compromise between magnitude and phase. The procedure in this paper meets these requirements through the use of an iterative computeraided design leading to an optimum set of parameters for a specified filter topology and is an extension of the technique described by Steiglitz (see ref. 6) for determining the optimum coefficients of a cascade filter having magnitude specifications alone. The extension makes possible the design of a new class of digital filters having the prescribed phase characteristics.

SYMBOLS

A	filter multiplier
\boldsymbol{D}_{k}^{i}	denominator of ith stage of $H(z)$ at $\Omega_{\mathbf{k}}$
$\mathbf{E}_k^{\mathbf{M}}$	magnitude error at $\Omega_{ m k}$
$\mathbf{E}_{\mathbf{k}}^{\boldsymbol{\phi}}$	phase error at $\Omega_{ m k}$
$\overline{\dot{e}}_k$	error vector at $\Omega_{\mathbf{k}}$
$\partial \overline{e}_k /\!\!/ \partial A$	derivative of error vector at $\Omega_{\mathbf{k}}$ with respect to zero frequency gain
f_k	frequency at kth specification point, Hz
f_s	sampling frequency, Hz
H(z)	unity gain discrete transfer function
$\left \mathbf{H}_{\mathbf{k}}\right $	magnitude of $H(z)$ at $\Omega_{\mathbf{k}}$
$\overline{\mathtt{H}}_k$	conjugate of $H(z)$ at Ω_{k}
$\partial \left H_{k} \right / \partial \vec{p}$	gradient vector of magnitude of $ \text{H(z)} $ at $ \Omega_k $ with respect to parameter vector
I()	imaginary part of quantity
i,,N	denotes filter stage

Jacobian at $\Omega_{\mathbf{k}}$, $\left[\mathbf{A}^* \frac{\partial \left| \mathbf{H}_{\mathbf{k}} \right|}{\partial \mathbf{p}} \middle| \frac{\partial \phi_{\mathbf{k}}}{\partial \mathbf{p}} \right]$ \vec{J}_k sample point k specification magnitude at Ω_k M_k N_k^i numerator of ith stage of H(z) at Ω_k \vec{p} parameter vector \vec{p}_i set of filter parameters for the ith stage, ai, bi, ci, and di qi(k) first system state of ith stage at kth sample point qi(k) second system state of ith stage at kth sample point R() real part of quantity input to ith stage at kth sample point ui(k) criterion functional, that is, $V(A,\vec{p})$ V criterion functional at Ω_k , that is, $V_k(A,\vec{p})$ v_k $\hat{\mathbf{v}}$ reduced criterion functional, that is, $V(A^*,\vec{p})$ A6/V6slope of criterion functional with respect to zero frequency gain $\partial V_k / \partial \vec{e}_k$ gradient vector of criterion functional at $\Omega_{\mathbf{k}}$ with respect to error vector at Ω_k \vec{w}_k weighting matrix at Ω_k $w_{\mathbf{k}}^{M}$ magnitude weighting at Ω_k $\mathbf{w}_{\mathbf{k}}^{\phi}$ phase weighting at Ω_k

dummy variable of ith stage at kth sample point

wⁱ(k)

Y(z) digital filter discrete transfer function

 $y_i(k)$ output of ith stage at kth sample point

z transform variable

 $m z_k$ discrete transform variable at $m ~\Omega_k$, e $^{j\pi\Omega_k}$

 θ_k specification phase at Ω_k , radians

λ collective phase weight

 ϕ_k phase of H(z) at Ω_k , radians

 $\partial \phi_k / \partial \vec{p}$ gradient vector of phase of H(z) at Ω_k with respect to parameter vector

 $\Omega_{\mathbf{k}}$ fractional frequency at kth specification point

An asterisk on a symbol denotes an optimum value. A circumflex denotes optimization with respect to A. A superscript T denotes the transpose.

DISCUSSION

The Filter Form

The fundamental advantages of the N-stage cascade canonical form of recursive digital filter whose signal flow graph is shown in figure 1 and which is described by the product operator $\frac{1}{2}$

$$Y(z) = A \prod_{i=1}^{N} \frac{1 + a_i z^{-1} + b_i z^{-2}}{1 + c_i z^{-1} + d_i z^{-2}}$$

$$Y(z) = AH(z)$$
(1)

are (1) its relative insensitivity to perturbations in the denominator coefficients, an important consideration in digital filters, especially of high order and particularly where finite register lengths (see ref. 1) are involved; (2) its simplicity of implementation; and (3) the simplicity of factoring the filter operator to determine its roots. This form has found extensive application in practical filters for signal processing, and a version employing serial arithmetic (ref. 7) is commercially available.

For completeness, an alternative description of the filter is given in terms of the system states $\mathbf{q_1^i}$ and $\mathbf{q_2^i}$ and clearly demonstrates the recursive nature of the filter. The set of difference equations describing the filter and required in developing a computer algorithm is presented. Thus, for the ith stage in figure 1 at the kth sample point

$$\begin{split} & w^{i}(\mathbf{k}) = \mathbf{A}_{i} \mathbf{u}_{i}(\mathbf{k}) - \mathbf{c}_{i} \mathbf{q}_{1}^{i}(\mathbf{k}) - \mathbf{d}_{i} \mathbf{q}_{2}^{i}(\mathbf{k}) \\ & \mathbf{q}_{1}^{i}(\mathbf{k}+1) = w^{i}(\mathbf{k}) \\ & \mathbf{q}_{2}^{i}(\mathbf{k}+1) = \mathbf{q}_{1}^{i}(\mathbf{k}) \\ & \mathbf{y}_{i}(\mathbf{k}) = w^{i}(\mathbf{k}) + \mathbf{a}_{i} \mathbf{q}_{1}^{i}(\mathbf{k}) + \mathbf{b}_{i} \mathbf{q}_{2}^{i}(\mathbf{k}) \end{split}$$

where

$$u_{i}(k) = y_{i-1}(k)$$

is the input to the ith stage and is identical to the output of the (i - 1) stage and

$$A_{i} = \begin{cases} A & \text{(i = 1)} \\ 1 & \text{(i \neq 1)} \end{cases}$$

The Synthesis Problem

The design problem considered in this paper can be stated as follows: When the magnitude and phase specifications (M_k and θ_k , respectively) at the kth fractional Nyquist frequencies $\Omega_k = 2f_k/f_s$ (where f_s is the sampling frequency in Hz) are known, determine the set of optimum parameters \vec{p}^* of an N-stage cascade filter having the form of equation (1) so that the resultant digital filter will have a minimum sum squared magnitude and phase error for all specified frequencies.

By constraining the filter topology, the optimum synthesis problem becomes one of parametric optimization with respect to a given criterion of fit. The composite criterion which can weight the magnitude and phase requirements independently and as functions of frequency is chosen as the inner product

$$V(A,\vec{p}) = \sum_{k} \langle \vec{e}_{k}, \vec{W}_{k} \vec{e}_{k} \rangle = \sum_{k} V_{k}$$
 (2)

where

$$\vec{\mathbf{e}}_{\mathbf{k}} = \begin{bmatrix} \mathbf{A} \mid \mathbf{H}_{\mathbf{k}} \mid & -\mathbf{M}_{\mathbf{k}} \\ \\ \\ \phi_{\mathbf{k}} - \theta_{\mathbf{k}} \end{bmatrix} = \begin{bmatrix} \mathbf{E}_{\mathbf{k}}^{\mathbf{M}} \\ \\ \mathbf{E}_{\mathbf{k}}^{\phi} \end{bmatrix}$$

is the error vector and

$$\vec{\mathbf{W}}_{\mathbf{k}} = \begin{bmatrix} \mathbf{W}_{\mathbf{k}}^{\mathbf{M}} & \mathbf{0} \\ \\ \mathbf{0} & \lambda \mathbf{W}_{\mathbf{k}}^{\phi} \end{bmatrix}$$

is the diagonal weighting matrix. Clearly, $V\left(A,\overrightarrow{p}\right)$ is a nonlinear function of the parameter vector $\overrightarrow{p} = \left(a_1,b_1,c_1,d_1,\ldots,a_N,b_N,c_N,d_N\right)^T$, which involves the 4N filter coefficients, and of the filter multiplier A.

The Minimization Algorithm

Through formal differentiation of the criterion function (eq. (2)) with respect to the multiplier A, the minimization procedure can be slightly simplified to that of finding the minimum of a reduced functional $\hat{V}(\vec{p}) = V(A^*,\vec{p})$ involving only 4N parameters. Thus

$$\frac{\partial V}{\partial A} = \sum_{k} \left\langle \frac{\partial \vec{e}_{k}}{\partial A}, \frac{\partial V_{k}}{\partial \vec{e}_{k}} \right\rangle = 2 \sum_{k} \left[\left| H_{k} \right| W_{k}^{M} \right| 0 \right] \vec{e}_{k}$$

and $\partial V/\partial A = 0$ implies

$$2\sum_{\mathbf{k}}\left|\mathbf{H}_{\mathbf{k}}\right|\mathbf{W}_{\mathbf{k}}^{\mathbf{M}}\!\left(\mathbf{A}^{*}\!\left|\mathbf{H}_{\mathbf{k}}\right|-\mathbf{M}_{\mathbf{k}}\right)=\mathbf{0}$$

or

$$A^* = \frac{\sum_{k} |H_k| W_k^M M_k}{\sum_{k} |H_k|^2 W_k^M}$$
 (3)

An additional necessary condition for existence of an extremum is that the gradient vector be zero; thereby, the optimum parameter vector \vec{p}^* is obtained. From equation (2)

$$\frac{\partial \hat{\mathbf{V}}}{\partial \vec{\mathbf{p}}} = 2 \sum_{\mathbf{k}} \left\langle \vec{\mathbf{J}}_{\mathbf{k}}, \vec{\mathbf{W}}_{\mathbf{k}} \vec{\mathbf{e}}_{\mathbf{k}} \right\rangle \tag{4}$$

where the (4N imes 2) Jacobian \vec{J}_k is

$$\vec{\mathbf{J}}_{k}^{T} = \nabla_{\vec{\mathbf{p}}} \vec{\mathbf{e}}_{k} = \left[\mathbf{A}^{*} \frac{\partial |\mathbf{H}_{k}|}{\partial \vec{\mathbf{p}}} \middle| \frac{\partial \phi_{k}}{\partial \vec{\mathbf{p}}} \right]^{T}$$
(5)

Clearly, each element of the gradient vector is the sum of two weighted functions of the magnitude and phase error. By writing

$$|H_{\mathbf{k}}|^2 = H_{\mathbf{k}}\overline{H}_{\mathbf{k}}$$

where \overline{H}_k is the conjugate of H_k evaluated at the fractional frequency Ω_k , it is readily shown (see ref. 6), where \overline{p}_i is the set of filter parameters for the ith stage, that

$$\frac{\partial \left| \mathbf{H}_{k} \right|}{\partial \vec{\mathbf{p}}_{i}} = \frac{1}{\left| \mathbf{H}_{k} \right|} \mathbf{R} \left(\mathbf{H}_{k} \frac{\partial \mathbf{H}_{k}}{\partial \vec{\mathbf{p}}_{i}} \right)$$

For the cascaded filter topology in terms of the elements of \vec{p}_i ,

$$\frac{\partial \left| \mathbf{H}_{k} \right|}{\partial \mathbf{a}_{i}} = \left| \mathbf{H}_{k} \right| \mathbf{R} \left(\frac{\mathbf{z}_{k}^{-1}}{\mathbf{N}_{k}^{i}} \right)$$

$$\frac{\partial \left| \mathbf{H}_{k} \right|}{\partial \mathbf{b}_{i}} = \left| \mathbf{H}_{k} \right| \mathbf{R} \left(\frac{\mathbf{z}_{k}^{-2}}{\mathbf{N}_{k}^{i}} \right)$$

$$\frac{\partial \left| \mathbf{H}_{k} \right|}{\partial \mathbf{c}_{i}} = -\left| \mathbf{H}_{k} \right| \mathbf{R} \left(\frac{\mathbf{z}_{k}^{-1}}{\mathbf{D}_{k}^{i}} \right)$$

and

$$\frac{\partial \left| \mathbf{H}_{k} \right|}{\partial \mathbf{d}_{i}} = - \left| \mathbf{H}_{k} \right| \mathbf{R} \left(\frac{\mathbf{z}_{k}^{-2}}{\mathbf{D}_{k}^{i}} \right)$$

where, with $z_k = e^{j\pi\Omega_k}$,

$$N_k^i = N^i(z_k) = 1 + a_i z_k^{-1} + b_i z_k^{-2}$$

and

$$D_k^i = D^i(z_k) = 1 + c_i z_k^{-1} + d_i z_k^{-2}$$

By letting

$$H_k = |H_k| e^{j\phi_k}$$

it follows that

$$\phi_{\mathbf{k}} = \mathbf{I} \left(\log_{\mathbf{e}} \mathbf{H}_{\mathbf{k}} \right)$$

whence

$$\frac{\partial \phi_k}{\partial \vec{p}} = I \left(\frac{\partial}{\partial \vec{p}} \log_e H_k \right) = I \left(\frac{1}{H_k} \frac{\partial H_k}{\partial \vec{p}} \right)$$

which takes on a particularly simple form for the cascade topology. For the ith stage parameters, in fact,

$$\frac{\partial \phi_{\mathbf{k}}}{\partial \mathbf{a_i}} = \mathbf{I} \left(\frac{\mathbf{z_k^{-1}}}{\mathbf{N_k^i}} \right)$$

$$\frac{\partial \phi_k}{\partial b_i} = I \left(\frac{z_k^{-2}}{N_k^i} \right)$$

$$\frac{\partial \phi_k}{\partial c_i} = -I \left(\frac{z_k^{-1}}{D_k^i} \right)$$

and

$$\frac{\partial \phi_k}{\partial d_i} = -I \begin{pmatrix} z_k^{-2} \\ D_k^i \end{pmatrix}$$

The special case of a one-stage (N = 1) filter is illustrated. Here

$$H_{k} = A \frac{1 + az_{k}^{-1} + bz_{k}^{-2}}{1 + cz_{k}^{-1} + dz_{k}^{-2}}$$

$$\hat{\mathbf{V}} = \sum_{\mathbf{k}} \left(\mathbf{A}^* \left| \mathbf{H}_{\mathbf{k}} \right| - \mathbf{M}_{\mathbf{k}} \right)^2 \mathbf{W}_{\mathbf{k}}^{\mathbf{M}} + \lambda \sum_{\mathbf{k}} \left(\phi_{\mathbf{k}} - \theta_{\mathbf{k}} \right)^2 \mathbf{W}_{\mathbf{k}}^{\phi}$$

and

$$\frac{\partial \hat{V}}{\partial a} = 2 \sum_{k} \left(E_{k}^{M} W_{k}^{M} \frac{\partial \left| H_{k} \right|}{\partial a} + \lambda E_{k}^{\phi} W_{k}^{\phi} \frac{\partial \phi_{k}}{\partial a} \right) = \sum_{k} \left| Q_{k}^{M} R \left(\frac{z_{k}^{-1}}{N_{k}^{i}} \right) + \lambda R_{k}^{\phi} I \left(\frac{z_{k}^{-1}}{N_{k}^{i}} \right) \right|$$

Similarly,

$$\frac{\partial \hat{V}}{\partial b} = \sum_{k} \left[Q_{k}^{M} R \left(\frac{z_{k}^{-2}}{N_{k}^{i}} \right) + \lambda R_{k}^{\phi} I \left(\frac{z_{k}^{-2}}{N_{k}^{i}} \right) \right]$$

$$\frac{\partial \hat{V}}{\partial c} = \sum_{k} \left[Q_{k}^{M} R \left(\frac{z_{k}^{-1}}{D_{k}^{i}} \right) + \lambda R_{k}^{\phi} I \left(\frac{z_{k}^{-1}}{D_{k}^{i}} \right) \right]$$

$$\frac{\partial \hat{V}}{\partial d} = \sum_{k} \left[Q_{k}^{M} R \left(\frac{z_{k}^{-2}}{D_{k}^{i}} \right) + \lambda R_{k}^{\phi} I \left(\frac{z_{k}^{-2}}{D_{k}^{i}} \right) \right]$$

where

$$Q_k^M = 2E_k^M W_k^M \left| H_k \right|$$

and

$$R_k^{\phi} = 2E_k^{\phi}W_k^{\phi}$$

are the weighted errors. It is obvious that the frequency intervals of the input data (specifications) need not be uniform and may, in fact, be intentionally unequal to allow for nonuniform frequency weighting.

Complementary Root Reflection and Stability

In deriving the frequency response of a discrete operator by letting z_k lie on the unit circle Γ , it is possible to take advantage of a unique property of the discrete transform pertaining to its magnitude when a root lying outside the unit circle is imaged or reflected into the unit circle. It is easy to show that the magnitude of a phasor $z-z_0$, where z_0 is a root of the discrete transform lying outside the unit circle, is equal to

$$\left|z-z_{0}\right|=\left|z_{0}\right|\left|z-\frac{1}{z_{0}}\right|;z\in\Gamma$$

Since z_0 has been assumed to be outside the unit circle, $1/z_0$ must be inside, the term $|z_0|$ correcting for magnitude changes. Thus, if in the optimization procedure a pole should stray outside the unit circle and thereby lead to an unstable filter, root reflection guarantees stability with no magnitude change. There is no analogous simple identity for the phase of a reflected root. Experience with the procedure has shown that provided the design requirements can be met by means of a stable filter, that is, that a feasible solution exists, an optimum will indeed be found through repeated application of root reflection.

The Computer Algorithm

A complete listing of the filter design algorithm, which is an adaptation of the program written by Steiglitz, is given in the appendix. The main program is termed STGZ3 which calls four principal subroutines: (1) FUNCT performs the functional and gradient computation for each iteration as well as putting out the final optimum parameters and plots, (2) FLPWL is a Fletcher-Powell conjugate gradient routine, (3) INSIDE computes root reflection, and (4) ROOTS determines the poles and zeros of the filter. Single-precision arithmetic has been employed.

When minimization of the functional has been attained in the first pass or the minimization algorithm has iterated 300 times, a test is made to ascertain that all the roots are within the unit circle, a necessary requirement for the poles for stability reasons and for the zeros to insure minimum phase. If the design should result in an unstable

configuration, the roots are reflected about the unit circle and minimization is resumed in a second pass. If a minimum does indeed exist and all the roots then lie within the unit circle, the program computes and prints out the frequency response and commences plotting.

Minimization is deemed to be achieved when the absolute difference in functionals between successive iterations $\epsilon = \left| \hat{V}_{new} - \hat{V}_{old} \right|$ or the norm of the gradient vector falls below preassigned limits. Convergence is generally fast for magnitude or phase filters but can be very slow for the case of compromise filters.

When the design specifications cannot be met after LIM iterations (see appendix), the program will stop; this situation indicates that the optimum could not be found and the resultant characteristic which may be unusable is plotted. Generally, feasible designs have been determined in less than 2000 iterations.

Minimization of the criterion function does not guarantee determination of a global minimum but rather determination of a local minimum. Depending upon the parameter vector utilized for initialization of the algorithm computation, different minima may be achieved. Experience has shown that stage-by-stage optimization, that is, utilization of the ith-stage optimum parameter vector as the initial parameter vector for the (i+1) stage of an N-stage filter, yields lower minimum values of the criterion function than does single-pass optimization.

APPLICATIONS

Linear-Phase Filter

This example considers a digital filter having application as a phase discriminator with a linear phase characteristic and arbitrary magnitude characteristic and is shown in figure 2. In this example all magnitude weights were set to zero and all phase weights to unity, the multiplier A being arbitrarily made unity since it has no effect on the phase characteristic.

The phase requirements were $\theta_k = 1 - 2\Omega_k$ $(0 \le \Omega_k \le 1)$, and a two-stage filter was specified. When an initial parameter vector $\vec{p} = (0,0,0,0.25,0,0,0,0)^T$ was used, the algorithm converged to the optimum, with $\epsilon = 10^{-4}$, in 52 iterations and a Control Data 6600 computer time of 14 seconds. The optimum parameter values computed were to four places

$$A = 1.0$$
 $a_1 = 0$
 $b_1 = -0.9871$
 $c_1 = 0$
 $d_1 = 0.0395$
 $a_2 = 0$
 $b_2 = -0.9871$
 $c_2 = 0$
 $c_3 = 0.0127$

It is interesting to note that the phase requirements were met to within 0.008π radian for approximately 95 percent of the frequency range.

Constant-Phase Filters

Two cases were considered to obtain filters having constant phases of $-\pi/2$ and $\pi/2$ radians over a frequency range $0.3 \le \Omega_{\rm k} \le 0.7$. As in the previous case, the form of the magnitude characteristic was of no concern; hence, zero magnitude weighting was specified. With the same initial parameter state used in the previous example, the first case (lag network) optimized in 1673 iterations and 42 seconds to yield a hyperbolic magnitude characteristic and phase errors of less than 0.0003π radian throughout the specified band.

The computed parameters for the lag case were

A = 1.0

A = 1.0

$$a_1 = 0.5580$$
 $b_1 = -0.1857$ $c_1 = -0.4752$ $d_1 = 0.0363$ $a_2 = 0.5580$ $b_2 = -0.1857$ $c_2 = -0.3712$ $d_2 = -0.5686$

The positive phase filter (lead network), however, took only 165 iterations and 17 seconds to yield the desired phase characteristic with errors nowhere exceeding 0.001π radian in the specified band.

The optimum filter parameters for this second case were determined to be

$a_1 = -0.4768$	$b_1 = -0.1548$	$c_1 = 0.5022$	$d_1 = -0.1082$
$a_2 = -0.4768$	$b_2 = -0.1548$	$c_2 = 0.4515$	$d_2 = -0.2008$

It is noted that for both cases, the phase weights outside the specified band were set to zero, and thereby allowed for arbitrary phase in these regions. Figures 3(a) and 3(b) show the resultant frequency characteristics for the lag and lead cases, respectively, of two-stage filters. The combination of the two filters, although they have antagonistic magnitude characteristics, suggests the possibility of a phase-splitting digital network.

Limited-Band Constant-Gain Linear-Phase Filter

The third example demonstrates a compromise design of a digital filter having constant-magnitude and linear-phase characteristics, over a limited frequency band, typical of phase discriminators. Here, except for $\lambda=0$, the specifications were stated as

$$\begin{aligned} \mathbf{M}_{\mathbf{k}} &= \begin{cases} 1 & \left(0.3 \leq \Omega_{\mathbf{k}} \leq 0.7\right) \\ 0 & \left(\text{Elsewhere}\right) \end{cases} \\ \theta_{\mathbf{k}} &= \begin{cases} 1 - 2\Omega_{\mathbf{k}} & \left(0.3 \leq \Omega_{\mathbf{k}} \leq 0.7\right) \\ 0 & \left(\text{Elsewhere}\right) \end{cases} \end{aligned}$$

Equal error and frequency weights were employed and the effects of changes in λ are shown in figure 4 for a two-stage design. Figure 4(a) shows the case of $\lambda=0$, that is, a magnitude-only filter being specified, and coincidentally yields the linear-phase-filter characteristic derived in the first example. (See fig. 2.) Figures 4(b) and 4(c) show the magnitude and phase characteristics for the cases of $\lambda=10$ and $\lambda=1000$, respectively. The increasing weight on phase and resultant degradation in the magnitude characteristic are shown. The optimum parameters were

 $\lambda = 0$:

$$A = 0.2063$$
 $a_1 = 0.0000$ $b_1 = -1.0000$ $c_1 = 0.0000$ $d_1 = 0.1539$ $a_2 = 0.0000$ $b_2 = -1.0000$ $c_2 = 0.0000$ $d_2 = 0.1539$

 $\lambda = 10$:

$$A = 0.3658$$

$$a_1 = -0.9754 \qquad b_1 = 0.7300 \qquad c_1 = 0.4529 \qquad d_1 = 0.7211$$

$$a_2 = 0.8632 \qquad b_2 = 0.5632 \qquad c_2 = -0.6119 \qquad d_2 = 0.7443$$

 $\lambda = 1000$:

$$A = 0.4232$$

$$a_1 = -1.1739$$
 $b_1 = 0.8489$ $c_1 = 0.7596$ $d_1 = 0.6691$ $a_2 = 1.1739$ $b_2 = 0.8489$ $c_2 = -0.7596$ $d_2 = 0.6691$

Low-Pass Zero-Phase Filter

The fourth example considers a compromise filter, having two and three stages, with specifications that are intentionally conflicting. A filter described by

$$\mathbf{M_k} = \begin{cases} 1.0 & \left(0.0 \le \Omega_{\mathbf{k}} < 0.5\right) \\ 0.5 & \left(\Omega_{\mathbf{k}} = 0.5\right) \\ 0.0 & \left(0.5 < \Omega_{\mathbf{k}} \le 1.0\right) \end{cases}$$

$$\theta_{\mathbf{k}} = \begin{cases} 0 & \left(0.0 \le \Omega_{\mathbf{k}} \le 0.5\right) \\ \text{Unspecified} & \left(\text{Elsewhere}\right) \end{cases}$$

is specified.

Figures 5 and 6 show the results for the two- and three-stage designs, respectively, with figures 5(a) and 6(a) showing the magnitude-only ($\lambda=0$) case. The degradation in the magnitude characteristics when greater emphasis is placed on the phase specifications is evident in figures 5(b) and 6(b) for $\lambda=10$ and in figures 5(c) and 6(c) for $\lambda=1000$. Comparison of figure 6 with figure 5 demonstrates the improvement brought about by increasing the number of stages. The optimum parameters for the two-stage filter were

 $\lambda = 0$:

$$A = 0.1196$$
 $a_1 = 1.0240$ $b_1 = 1.0000$ $c_1 = -0.1713$ $d_1 = 0.7676$ $a_2 = 1.0240$ $b_2 = 1.0000$ $c_2 = -0.5324$ $d_2 = 0.2286$

 $\lambda = 10$:

$$A = 0.4879$$

$$a_1 = 0.2018$$

$$b_1 = 0.6684$$

$$c_1 = 0.3560$$

$$d_1 = 0.4612$$

$$a_2 = 0.6597$$

$$b_2 = 0.4335$$

$$c_2 = 0.0806$$

$$d_2 = 0.7671$$

 $\lambda = 1000$:

$$\mathbf{A}=\mathbf{0.5343}$$

$$a_1 = 0.0205$$

$$b_1 = 0.7169$$

$$c_1 = -0.0836$$

$$d_1 = 0.6255$$

$$a_2 = 0.6286$$

$$b_2 = 0.7905$$

$$c_2 = 0.2123$$

$$d_2 = 0.6681$$

The optimum parameters for the three-stage filter were

 $\lambda = 0$:

$$A = 0.0510$$

$$a_1 = 0.8537$$

$$b_1 = 1.0000$$

$$c_1 = -0.1068$$

$$d_1 = 1.0000$$

$$a_2 = 0.8537$$

$$b_2 = 1.0000$$

$$c_2 = -0.4046$$

$$d_2 = 0.5990$$

$$a_3 = 0.8537$$

$$b_3 = 1.0000$$

$$c_3 = -0.6799$$

$$d_3 = 0.2069$$

 $\lambda = 10$:

$$A = 0.5109$$

$$a_1 = 1.3302$$

$$b_1 = 0.5515$$

$$c_1 = -0.1731$$

$$d_1 = 0.8097$$

$$a_2 = 0.6844$$

$$b_2 = 0.7157$$

$$c_2 = 1.1880$$

$$d_2 = 0.5850$$

$$a_3 = -0.0373$$

$$b_3 = 0.7012$$

$$c_3 = 0.3825$$

$$d_3 = 0.5262$$

 $\lambda = 1000$:

A = 0.4515

$a_1 = 1.5107$	$b_1 = 0.5286$	$c_1 = -0.1771$	$d_1 = 0.8972$
$a_2 = 0.5825$	$b_2 = 0.7490$	$c_2 = 1.3094$	$d_2 = 0.4191$
$a_3 = -0.1663$	$b_3 = 0.7485$	$c_3 = 0.2002$	$d_3 = 0.6393$

A three-stage design of this example is used to demonstrate the existence of two distinct local minima, dependent upon the initial parameter vector. In the first case, a single-pass optimization was accomplished with $\vec{p}=(0,0,0,0.25,0,0,0,0)^{\rm T}$ for the initial parameter vector and resulted in the optimum filter shown in figure 6(a). In the second case, a stage-by-stage optimization was accomplished by utilizing the optimum parameter vector from a two-stage design for the initial parameter vector of a three-stage design and resulted in the optimum filter shown in figure 7. Comparison of these results demonstrates the existence of two distinct local minima, the stage-by-stage minimization yielding superior results.

CONCLUDING REMARKS

A method has been developed for a computer-aided design of cascade canonical digital filters having prescribed magnitude or phase characteristics or a compromise between the two. The method, which uses an unconstrained minimization algorithm, allows for arbitrary error and frequency weighting. Representative designs of phase and compromise filters have demonstrated the utility of the technique. Although convergence is generally fast for magnitude phase filters, it may be slow for the case of compromise filters.

Langley Research Center,

National Aeronautics and Space Administration, Hampton, Va., February 17, 1972.

APPENDIX

PROGRAM LISTING

This appendix contains a program listing written for the Control Data 6600 computer at the Langley Research Center, Hampton, Virginia, and is an adaptation of that written by Kenneth Steiglitz at Princeton University for the design of specified magnitude-only filters.

```
PROGRAM STG73 (INPUT. PUTFUT, TAPE5 = INPUT. TAPE6 = CUTPUT. PUNCH)
                                                                                             0013
000003
                EXTERNAL FUNCT
                                                                                             0014
000003
                DIMENSION H(184).X(16).G(16)
                                                                                             CC15
                CCMMCN/RAW/W(1(0).Y(100).M.PHASED(100).ALAMDA.FR.WTM(100).
000003
                                                                                             0016
               C WIP(100).KTYP
                                                                                             0017
000003
                CCMMCN/RAWI/ICALL.KCALL.LIM
                                                                                             0019
000003
                CALL CALCOMP
000004
                CALL LFR )Y
                                                                                             0020
                WRITE (6.51)
000005
                                                                                             0021
000011
             51 FORMAT(* INPUT DATA*)
                                                                                             0022
000011
                M = 0
                                                                                             0023
000012
             36 M=M+1
                                                                                             0024
                PEAC(5,21)&(M),Y(M),PHASEC(M),WTM(M),WTP(M)
000014
                                                                                             0025
000031
             21 FCPMAT(5F10.5)
                                                                                             0025
                WP I TF (6.72) M. W(M) . Y(M) . PHASEC(M) . WTM (M) . WTP (M)
000031
                                                                                             0027
000051
             22 FORMAT(* I=*, I ? .* W=* F 7.4.* Y=* F 7.4.* PHASFD=*, F7.4.
                                                                                             0028
               C * WTM=*.F7.4.* WTP=*.F7.4)
                                                                                             0029
000051
                IFIMIMI.LT.1.CCIGCT030
                                                                                             0030
000054
                DO 15 J=1.16
                                                                                             0031
000056
             15 X(J)=0.00
                                                                                             0032
000061
                X(4) = .25
                                                                                             0033
000062
            95 REAC(3.50) L.LIM. EST. EPS. HMAX. ALAMDA, ER, KTYP
              FORMAT(215.5F1C.5.11C)
000106
                                                                                             0035
000106
                IF(FR.LT..001) FR=1.
                                                                                             0035
000112
                N = 4 *1
                                                                                             0037
                IF(FOF,5) 999,888
000113
                                                                                             0038
           388 CONTINUE
000117
                                                                                             0039
                WPITE (6.61) L. LIM. FST . FPS . FMAX, FR, ALAMCA
000117
             61 F()KMAT(* L=*.13.* L[M=*.15.* EST=*.F10.5.* FFS=*.F10.5.
000141
               C* hMAX=*,F10.5,* FRECRANGE=*,F10.5,* LAMBDA=*,F10.5)
                                                                                             0042
000141
                TCALL = 0
                                                                                             0043
             98 KCALL =0
000142
000143
                CALL FLPWL(FUNCT.N.X.F.G.FST.FPS.FC.IEP.H)
000155
                CALL POOTS (N.X)
                                                                                             0045
000157
                CALL INSIDE(N.X.KFLAG)
                                                                                             0045
000152
                WRITE (6.26) TER . KFLAG . TC ALL . KCALL
             26 FOPMAT(* [FR=*.15.* KFLAG=*.15.* ICALL=*.15.* KCALL=*.15)
000176
                IFIKCALL.GT.3001 GO TO SR
000176
000202
                IF ( (KFLAG.NF.C.CP.IER.NE.C).AND. (CALL. LF. LIM) GC TC 98
000213
                CALL RESTSIN.X)
                                                                                             C050
000215
                ICALL =-10
                                                                                             0.051
000215
                CALL FUNCTIN, X.F.G. HMAX)
                                                                                             CCF 2
                SUTHER
                                                                                             20,25
000222
          959 CALL CALPLT(C., 0., 999)
                                                                                             00 56.
000223
                STOP
                                                                                             CCcr
000226
                                                                                             COFF
000230
                END
```

```
SUBROUTINE FUNCTION .X .F .G. HMAX)
                                                                                                 0057
 000010
                 PIMENSICY CMEGA(200).PHASEX(200).AMAG(200).PHE(100).PHA(100)
                                                                                                 0058
 000010
                 DIMENSION XPL (200). YPL (200). CX(200). CY(200)
                                                                                                 0059
 000010
                 DIMENSION H(184).X(16).0(16).VHT(100).F(100)
                                                                                                 0060
 000010
                 COMPLEX 70PAR.7C.77CUR.77CUP2
                                                                                                 0061
 000010
                 CLMPLEX
                             7(100).TUM(100.4).DEN(100.4).D.QBAR.ZCUR.ZCURZ.ONEG
                                                                                                 0062
 000010
                 CCMMC N/RAW/W(1CC).Y(10C).M.PHASED(1CO).ALAMDA.FR.WTM(100).
                                                                                                 0063
                   WIP(100).KTYP
                                                                                                 0064
000010
                 CEMMINIPAWI/ICALE . KCALL . LIM
000010
                 UNEC=CMPLX(1.00.0.00)
                                                                                                 0066
000012
                 PI=-3.14150255359670
                                                                                                 0067
000014
                 K=1/4
                                                                                                 0068
00 )015
                 IF ( ICALL. NE. O) GOTC101
                                                                                                 0059
000015
                 DC 102 I=1.M
                                                                                                 0070
             102 Z(I) = CSXP(CMPLX(0.00.w(I)*PI))
000030
                                                                                                 0071
000 140
             101 A1=0.00
                                                                                                 0072
000041
                 A2=0.00
                                                                                                 0073
000042
                 PO 40 T=1.4
                                                                                                 0074
000043
                 7063=7(1)
                                                                                                 0075
000044
                 ZCURZ=ZCUR*ZCUR
                                                                                                 0076
000053
                 J= CMPEX(1.00.0.00)
                                                                                                 0077
200156
                 DO 34 J=1.K
                                                                                                 0078
                 J4 = (J-1) *4
00 1057
                                                                                                 0079
                 TUM(1.J)=1.00+X(J4+1)*/CUR+X(J4+2)*/CUR?
0000-61
                                                                                                 0080
000103
                 DEN([.J)=1.00+X(J4+3)*ZCUP+X(J4+4)*ZCUP2
                                                                                                 0081
000120
              0082
000147
                 CPAR= CUNIG(0)
                                                                                                 0083
000152
                 PAHCE ( 1 ) THY
                                                                                                 0084
000150
                 \Delta 2 = \Delta 2 + YHT(T) # V TM(T)
                                                                                                 0085
000143
                 YHT(I) = SORT(YHT(I))
                                                                                                 0086
000167
             40 \Delta! = \Delta! + YHT(I) *Y(I) *WTM(I)
                                                                                                 0087
000221
                 IF (KTYP. ME.O) OF TO AA6
                                                                                                 0088
205000
                 A = A 1 / A ?
                                                                                                 0089
                 GC TC 657
000204
                                                                                                 0090
                  Δ=1.
000205
           465
                                                                                                 0091
000207
           647
                 CONTINUE
                                                                                                 0092
000207
                 OC 412 I=1.M
                                                                                                 0093
115060
                 77064=7111
                                                                                                 0094
000214
                 770U22=270UR#770UR
                                                                                                 C095
                 70=CMPLX(1..0.)
000221
                                                                                                0096
                 PHAS= O.
000224
                                                                                                 0097
000225
                 DC 611 J=1.K
                                                                                                 0038
000226
                 347 = (3 - 1) * 4
                                                                                                0099
000230
                 704 AF = CNEO+X(J47+1) #72CUR+X(J47+?) #77CUP2
                                                                                                0100
000247
                 741=798Ak
                                                                                                0101
000251
                 7 42 = ( MPL X ( ) . . - 1 . ) * 70 F AR
                                                                                                0102
007751
                 PHAS = PHAS + ATAN 2 ( ZA2 , ZA1 )
                                                                                                0103
000265
                 70=70*7 38AF
                                                                                                0104
000273
                 708 #R = ( N=0+X ( J4Z+3)*72CUR+X (J47+4)*77CUP2
                                                                                                0105
000315
                 7 A 1 = 7 3 3 A P
                                                                                                0106
000317
                 ZA?=CMPLX(0..-1.)*ZQBAP
                                                                                                0107
000327
                 PHAS=PHAS-ATAN 2(7A2.7A1)
                                                                                                0108
000322
                 70=20/73HAF
                                                                                                0109
000342
           611
                CONTINUE
                                                                                                0110
000350
                 PHA(I)=-PHAS/PI
                                                                                                0111
000353
           512 PHF (I)=PHA (I)-PHASEC(I)
                                                                                                0112
000360
                 on 57 J=1.16
                                                                                                0113
000361
             57 G(J)= ). 30
                                                                                                0114
000364
                 VI = 0.
                                                                                                0115
000355
                 V2=0.
                                                                                                0116
000365
                PO 42 I=1.M
                                                                                                0117
0.00367
                 7CUR=7(1)
                                                                                                0119
000372
                 70092=700P*200F
                                                                                                0119
030377
                 YHI(I) = A * YHI(I)
                                                                                                0120
000402
                rac{1}{2} = Y + T(I) - Y(I)
                                                                                                0121
000405
                V1=V1+E(1)*E(1)*WTM(1)
                                                                                                0122
                V2=V2 FPHF(I)*PHF(I)*WTF(I)
000410
                                                                                                0123
000414
                P=F(1) #W FM(1)
                                                                                                0124
                T = PHF ( T ) * WTP ( T ) * 2 . * A L A M C A
000410
                                                                                                0125
```

```
003422
                DC 422J=1.K
                                                                                               0126
000423
                J4=(J-1)*4
                                                                                               0127
000425
                 )=2.*<*YHT([]/TUM([,])
                                                                                               0128
                                                                                               0129
000441
                G(J4+1)=G(J4+1)+J*ZCLR
000451
                G(J4+2)=G(J4+2)+0*70LR2
                                                                                               0130
000461
                0=- 7. * " * YHT ( 1 ) / FEN ( 1 . J )
                                                                                               0131
000475
                G(J4+3)=G(J++2)+J*7CUR
                                                                                               0132
000505
                G(14+4)=G(14+4)+0*7CUP2
                                                                                               0133
000514
                CLNTINIIE
                                                                                               0134
00051~
                ") 7 42 J=1.K
                                                                                               0135
000520
                14=(1-1) #4
                                                                                               0136
003522
                G(J4+1)=G(J4+1)+T*\Lambda IMAG(ZCUP/TUM(I,J))
                                                                                               0137
000527
                G(14+2)=G(J4+2)+T*AI*AG(7(U#2/TUM(I,J))
                                                                                               0138
000554
                G(J4+3) = 3(J4+2)+T*AI*AG(-7(UE/UEN(I,J))
                                                                                               0139
000571
                G(J4+4)=S(J4+4)+T*AI*A((-7CLF2/DEN(I.J))
                                                                                               0140
           42
003504
                CINTINUE
                                                                                               0141
000613
                F=V1+ALAMDA#V2
                                                                                               0142
000616
                 ICALL = ICALL+1
                                                                                               0143
000620
                 KCALL = KCALL +1
000621
                 IF(KCALL.GT. GC)PFTURN
                 IF((ICALL/10)*10.EQ.ICALL-1)WRITE(6.25)ICALL.F.(3(J).J=1.N)
000624
                                                                                               0144
000657
             25 FCRMAT(* CALL NC.*.[4,* F=*.F]5.9/( 25X, 4F]5.8))
                                                                                               0145
000657
                 IFIICALL.GT.?OCC) GO TO 450
000663
                 IF ( IC ALL . GT . O ) RETURN
                                                                                               0147
000665
                GO TO 449
000566
            456 IF(ICALL.GT.LIM+1) GC TC 449
000573
                RETURN
          C.....PRINT OUT
                                                                                               0148
000673
            449 WRITE[6,50]F
                                                                                               0149
000701
             50 FORMAT(* FINAL FUNCTION VALUE =*.F15.8)
                                                                                               0150
002701
                 4RITF (6,51) A
                                                                                               01-1
002707
                                                                                               0152
             51 FORMAT(* A=*.F15.8)
00 17 07
                 WPITE(6.52)(X(J).J=1.N)
                                                                                               0153
002731
             52 FORMAT(* FINAL X =*/(* *.4F15.6))
                                                                                               0154
000731
                 WRITE(6,54)(G(J),J=1.N)
                                                                                               0155
000753
             54 FORMAT(* FINAL GRADIENT =*/(* *.4F15.8))
                                                                                               0156
                DO 55 I=1.M
000753
                                                                                               0157
000760
             55 WRITE(6.56)I.W(I).Y(I).YHT(I).E(I).PH4SED(I).PH4(I).PHE(I)
                                                                                               0158
001211
                FURMAT(* [=*.[].* W=*.F8.5.* Y=*.F8.5.* YHT=*.F8.5.* E=*.F8.5.
                                                                                               C153
               C * PHASED=*, F8.5, * PHA=*, F8.5, * PHE=*, F8.5)
                                                                                               0150
                                                                                               0161
001011
                 WF [ TE ( 5,59 ) K
001016
             59 FORMATI* FINAL TABLE FOR A*,12,* STAGE FILTER*)
                                                                                               0162
001016
                 . O = E : 11MY
                                                                                               0163
001017
                YMAX33=0.
                                                                                               0164
001020
                 YMAX11=0.
                                                                                               0165
001021
                 S=FR/200.
                                                                                               0166
                DO 60 I=1.201
001023
                                                                                               0167
001027
                FFFQ=S*FLOAT(I-1)
                                                                                               0168
001032
                ZCUR= CEXP( CMPLX(0.CO.FREG*PI))
                                                                                               0169
001040
                ZCUR2=ZCUR*ZCUR
                                                                                               0170
001045
                Q = CMPLX(1.00.C.OC)
                                                                                               0171
00105)
                PHASE =0.00
                                                                                               0172
001051
                DC 61 J=1.K
                                                                                               0173
001055
                 14=(1-1) #4
                                                                                               0174
001057
                QHAR=UNEO+X(J4+1) *ZCUR+X(J4+2) *ZCUR2
                                                                                               0175
001 176
                \Delta 1 = OB \Delta P
                                                                                               0176
001100
                 A2=CMPLX(0.00,-1.00)*QEAR
                                                                                               0177
001110
                PHASE = PHASE + ATAN2 (A2. A1)
                                                                                               0178
001114
                Q=C *QPAK
                                                                                               0179
                QBAR=GNFO+X(J4+3)*ZCUR+X(J4+4)*ZCUR2
001122
                                                                                               0180
001144
                 A1=CRAR
                                                                                                C191
                                                                                               0182
001146
                 A2=CMPLX(0.00.-1.00)*QBER
001156
                 PHASE = PHASE - ATAN2 (A2, A1)
                                                                                               0183
001152
             61 0=0/0849
                                                                                               0194
001177
                                                                                                0195
                A1 = Q * CCNJG(Q)
001207
                \Delta 1 = \Delta * SQRT(\Delta 1)
                                                                                               0186
001212
                PHASE = - PHASE / PI
                                                                                                C187
001214
                CMEGALI1 = EPEQ
                                                                                               0138
001216
                 \Delta M \Lambda G(I) = \Delta 1
                                                                                                0189
                PHASEX(I)=PHASE
                                                                                               0190
001217
```

```
001221
                IF(FHASE-YMAX33) 301.301.401
                                                                                           0191
001226
           4C1 YMAX33=PHASE
                                                                                           0192
           3C1 CONTINUE
001230
                                                                                           0193
                 IF(PHASE-YMIN33) 402,302,302
 001230
                                                                                           0194
001233
           4 C 2
                YMIN33=PHASE
                                                                                           0195
           302 CCNTINUE
 001235
                                                                                           0196
001235
                IF(A1-YMAX11) 300.360.400
                                                                                           0197
           400 Y"AX11=A1
001240
                                                                                           0198
           3CG CONTINUE
001242
                                                                                           0199
001242
             6C WRITE (5,62) FREC, PHASE, AT
                                                                                           0200
             62 FORMAT(* W=*.F15.8.* PHASE/PI=*.F15.8.* YHT=*.F15.8)
001251
                                                                                           0201
          C SCALE COMPUTATIONS
                                                                                           0202
001261
                IYMAX11=YMAX11+.9599
                                                                                           0203
001264
                YMAX1 = FL \cap AT(IYMAX11)
                                                                                           0204
001256
                IE(HMAX.EQ.O.) GO TO 332
                                                                                           0205
001267
                YM\Delta X1 = HM\Delta X
                                                                                           0206
           333 CONTINUE
001270
                                                                                           0207
                1YMAX33=YMAX33+.699
001270
                                                                                           0208
001273
                YMAX7 = FLOAT(IYMAX73)
                                                                                           0209
001275
                IYMIN33=YMIN33-.9999
                                                                                           0210
001300
                YMIN3=FLDAT(IYMIN33)
                                                                                           0211
001301
                AXE=106 F/1FS/21
                                                                                           0212
001303
                AYM=1 OHMAGNITUDES
                                                                                           C213
001304
                AFR = 200. *FR
                                                                                           0214
001306
                NFR = 200
                                                                                           0215
          C MAGNITUDE (COMPUTED) - FRECUENCY PLOT
                                                                                           0216
001307
                CALL INFOPLTIG.NER.(MEGA.1.AMAG.1.C., FR.C., YMAX1.C.5,-10.4XM.-10.
                                                                                           0217
               C AYM.OL
                                                                                           0218
          C MAGNITURE (DESIRED) - EPEQUENCY PLOT
                                                                                           0213
001327
                CALL INFOPLT(1.M.W.1.Y.1. C..FF.C..YMAX1.3.5.+1C.AXM,+10.AYM,11)
                                                                                           0220
001347
                AYM=1 OH PHASE / FT
                                                                                           0221
          C PHASE-FREQUENCY PLCT
                                                                                           0222
001351
                CALL INFOPLICANFF. IMFCA.1.FHASEX.1.O..FF.YMIN3.YMAX3.O.5.-10.
                                                                                           0223
               ( AXM.-1J.AYE.O)
                                                                                           0224
         C PHASE (CISTRED) - EREQUENCY PLCT
                                                                                           0225
               001370
                                                                                           0226
               C AXM.-10.AYM.111
                                                                                           0227
                PETHEN
001410
                                                                                           0228
001411
                END
                                                                                           0229
                SUBSTRUCTIVE ELPAL (FUNCT.A.X.F.G.EST.EPS.LI4IT.IER.H)
                                                                                           0230
                DIME: STON H(1).X(1).C(1)
000015
                                                                                           0231
                COMMIN/RAWI/! CALL . KC ALL . LIM
000015
000015
                CALL FUNCTION, X.F.G. HMAX)
                                                                                           0233
                TELKCALL.GT.3001 GO TO 723
000027
000032
                IFFICALL.GT.LIMI (0 TO 723
               GO TO 617
000035
000035
            723 IF9=3
001037
                PETURN
000037
            917 IFR=0
000041
                KCUNT=0
                                                                                          0235
000041
                12 = 1 + V
                                                                                          0236
000042
                √ 3 = √2 + √
                                                                                          0237
020043
               A 41 = A 3 + 1
                                                                                          C238
000045
                K = N 3 ]
                                                                                          0239
000047
                ກຄ 4 J=1.N
                                                                                          0240
00015)
               H(K)=1.00
                                                                                          0241
030153
                \Lambda J = \Lambda - J
                                                                                          0242
000054
                [F(NJ) 5.5.2
                                                                                          0243
00)055
               70 3 L=1.NJ
                                                                                          0244
000063
                KI = K + L
                                                                                          0245
```

000061	3	H(Kt)=0.00		0246
000066	4	K=KL+1		0247
000072	5	KCUNT=KCUNT+1		0248
	,			
00)0 74		WRITE (5.501) KOUNT		0249
000101	501	FORMAT(* KOUMT=*.15)		0250
000101		าLDF=F		0251
000104		∩ ⊆ ⊆ J=1 • N		0252
000107		K = N + J		0253
000110		H(K)=G(J)		0254
000114		K=K+N		0255
000115		H(K) = X(J)		0255
000121		K=1+1/3		0257
000122		T=C.00		0258
000123		DF 3 (=1.V		0259
000124		T=T-G(1)#H(K)		0260
000131				
		IF(L-J) 0.7.7	•	0261
000134	t ^c	K=<+'4+l		0262
000137		gn ta a		0263
000137	7	K = K + 1		0264
000141	٦	CENTINUT		0265
000144	6	H(J) = T		0266
000150	,			
		DY=C.00		0267
000150		CO.O=M RNH		0268
000151		GNR M= 0.00		0269
000153		DO 10 J=1.N		0270
000154		HNRY=HNRM+ ABS(H(J))		0271
000160		GNRM=GNRM+ ABS(G(J))		0272
000163	10	DY = DY + H(J) * G(J)		0273
000173	10			
		IF(OY) 11.51.51		0274
000174	11	IF(HNRM/GNRM-EPS) 51.51.12		0275
000200	12	FY=F		0276
105000		ALFA=2.00*(FST-F)/DY		0277
000204		AMB DA = 1.00		0278
000205		IF(ALFA) 15.15.13		0279
000207	13	IF(ALFA-AMBDA) 14.15.15		
				0280
000212	14	AMBCA = ALFA		0281
000214	15	ALF4=0.00		0282
000215	16	FX=FY		0283
000216		DX = CY		0284
000223		DC 17 I=1.N		0285
000222	17	X(I)=X(I)+AMBCA*H(I)		0286
000231	• .	CALL FUNCT(N, X, F, G, HMAX)		
				C289
000243		IF(KCALL.GT.30C) GO TO 724		
000246		IF(ICALL.GT.LIM) GO TO 724		
000251		GN TO 918		
000251	724	IER =3		
000253		RETURN		
000253	518	FY=F		
000254		0Y=C.00		0292
000255		DO 18 I=1.N		0292
	1.0			
000257	18	DY = DY + G(I) * H(I)		0294
000266		IF(DY) 19.36.22		0297
000267	19	IF(FY-FX) 20.22.22		0298
000272	20	AMBDA = AMBCA + ALFA		C299
000274		ALFA= AMBDA		0300
000275		FRROR=1.E10		0301
000276		IF(HNRM*AMBDA-EPROR)16.15.21		0302
000778	2.1			
	21	TER=2		0303
000304		RETURN		0304
000304	22	T = 0 • 0 0		0305
000305	23	IF(AMBDA) 24,36,24		0306
000306	24	7=3.00*(FX-FY)/AMBDA+DX+DY		0307
000314		ALFA=AMAX1(ABS(Z), ABS(DX), ABS(DY))		0308
000326		DALFA=Z/ALFA		0309
000000		Sugar Eragin		9907

000327 000333 000335 000340 000351 000356 000366 000400 000403	25 26	DALFA=CALFA*DALFA-DX/ALFA*CY/ALFA IF(DALFA) 51.25.25 W=ALFA* SQRT(CALFA) ALFA= (DY+W-Z)*AMBDA/(DY+2.CO*W-DX) DO 26 I=1.N X(I)=X(I)+(T-ALFA)*H(I) CALL FUNCT(N.X.F.G.HMAX) IF(KCALL.GT.300) GD TO 725 IF(ICALL.GT.LIM) GD TO 725		0310 0311 0312 0313 0314 0315 0320
000406 000406	725	GO TO 919 : IER=3	·	
000410		RETURN		
000410	919	F [F(F-FX) 27.27.28		
000413	27	IF(F-FY) 36.36.28		0323
000416	2.8	DAL FA = 0 • 0 0		0324
000417		DG 29 I=1.N		0325
000421	29	DALFA = DALFA + G(I) * H(I)		0326
000430	2.0	IF(CALFA) 30,33,33		0329
000431 000434	3 C 3 1	IF(F-FX) 32.31.33		0330
000436	32	IF(CX-CALFA) 32,36.32 FX=F		0331 0332
000437	32	DX=CALFA		0333
000440		T=ALFA		0334
000442		AMBCA = ALFA		0335
000443		GO TO 23		0336
000443	33	IF(FY-F) 35.34.35		0337
000445	34	IF(DY-DALFA) 35.36.35		0338
000447	35	FY=F		0339
000450		DY = CALFA		0340
000451		AMBCA = AMBDA - ALFA		0341
000454	7.4	GO TO 22		0342
000454 000456	36	∩∩ 37 J=1.N K=N+J		0343 0344
000457		H(K)=G(J)-H(K)		0344
000463		K=K+N		0346
000464	37	H(K) = X(I) - H(K)		0347
000472		IF(OLDF-F+FPS) 51.38.38		0348
000476	3.8	I FR =0		0349
000477		IF(KOUNT-N) 42.39.39		0350
000501	39	T=0.00		0351
000502 000503		Z=0.00 DC 40 J=1.N		0352
000504		K=N+J		035 <u>3</u> 0354
000705		M=H(K)		0355
000510		K=K+^,		0356
000511		T=T+ APS(H(K))		0357
000514	40	7 = 7 + w + H (K)		0358
000523		IF(HNRM-EPS) 41.41.42		0359
000526	41	IF(T-FPS) 56.56.42		0360
000531	42	IF(KCUNT-LIMIT) 43,57,50		0361
000534	43	ALFA=C.(·)		0362
000535		no 47 J=1.N		0363
000537 000540		K=J+N3 W=C.00		0364 0365
000542		DC 44 L=I •N		0366
000543		KI = N FI.		0367
000544		W=W+H(KL)*H(K)		0368
000552		IF(L-J) 44,45,45		0369
000554	44	K = K + N - L		0370
C00557		GC TO 45		0371
000557	45	K = K + 1		0372
000561	46	CONTINUE		0373
000564 000565		K=N+J ALFA=ALFA+W*H(K)		0374 0375
1/10/07		PETE PERMITTION		0319

```
000572
                H(J)=W
                                                                                              0376
           47
000576
                IF ( Z*ALFA) 48.1.48
                                                                                              0377
000600
                                                                                              0378
           48
                K = N 31
000602
                90 49 L=1.N
                                                                                              0379
                                                                                              0380
000503
                KI = N2 + 1
000605
                DO 49 J=L.N
                                                                                              0381
                                                                                              0382
000606
                NJ = N2 + 1
000607
                H(K)=H(K)+H(KL)*H(NJ)/Z-H(L)*H(J)/ALFA
                                                                                              0383
000525
                                                                                              0384
           49
                K = K + 1
000633
                GO T) 5
                                                                                              0385
                IFP=1
                                                                                              0386
000634
           5.0
000636
                PETURN
                                                                                              0387
                00 52 J=1.N
                                                                                              0388
000636
           51
000640
                K=N2+ J
                                                                                              0389
                X(J)≈H(K)
                                                                                              0390
000641
           5.2
000647
                CALL FUNCTIN.X.F.G.HMAX)
                                                                                              0393
                IF(KCALL.GT.30C) GO TO 726
000661
000664
                IF(ICALL.GT.LIM) GO TO 726
000557
                GO TO 920
000667
            726 IFR=3
                PETURN
000671
000671
            926 IF(GNRM-FPS) 55.55.5?
                IF(IFR) 56.54.54
                                                                                              0396
000674
           53
000676
           54
                IFR =-1
                                                                                              0397
                GC TO 1
007700
                                                                                              0398
000700
           55
                [FR=)
                                                                                              0399
                RETURN
000701
           56
                                                                                              0400
000702
                FND
                                                                                              0401
```

```
SUBROUTINE INSIDE(N, X, KFLAG)
000006
                DIMENSION X(16)
000006
                J=-1
000006
                KFLAG=0
000007
             10 J=J+2
000011
                IF( J.GT.N) RETURN
000014
                E=-.500*X(J)
                C=X(J+1)
000016
                DISC=E*E-C
000020
                IF(DISC.LE.O.00)GOTO20
000022
         C....REAL ROOTS
000024
                DISC= SQRT(DISC)
000025
                R1=B+DISC
                R2=B-DISC
000027
000031
                CRI = ABS(R1)
                DR2= ABS(R2)
000033
                IF(DR1.LE.1.00.AND.DR2.LE.1.00)GOT010
000035
000051
                KFLAG=1
000051
                IF(DR1.GT.1.00)R1=1.00/R1
                IF(DR2.GT.1.00)R2=1.00/R2
000054
                X(J) = -1.00*(R1+R2)
000060
000064
                X(J+1)=R1*R2
000066
                GCTO10
         C.....COMPLEX ROOTS
             20 IF(C.LE.1.00)G0T010
000066
000071
                KFLAG=1
                C=1.00/C
000071
000072
                X(J+1)=C
000074
                X\{J\}=X\{J\}*C
000076
                GOT 01 0
000077
                FND
```

APPENDIX - Concluded

	SUBROUTINE RODTS (N.X)	0433
000005	DIMENSICN X(16)	04 34
000005	WRITE(6,40)	C4 35
000010	40 FORMAT(* ROOTS*/6X,*REAL*,11X,*IMAG*,11X,*REAL*,11X,*IMAG*)	0436
000010	J=~1	0437
000011	10 $J = J + 2$	0438
000013	IF(Jegten) RETURN	C4 39
000017	B=500*X(J)	C440
000021	C=X(J+1)	C441
000023	DISC=B*B-C	0442
000025	IF (DISC.LE.0.00) GO TO 20	0443
	CREAL RCOTS	0444
000027	DISC= SORT(DISC)	C445
000030	R1≈B+DISC	C446
000032	R2=B-D15C	0447
000035	WRITE(6.30)R1.R2	0448
000044	30 FORMAT (* *.F15.8.15x.F15.8)	0449
000044	607010	0449
000044	CCOMPLEX ROOTS	0450
000046	20 DISC= SORT(-1.00*DISC)	0451
000052	DI SC M=-1.00*DI SC	0453
000055	WRITE(6.50)B.DISC.B.DISCM	
000070	50 FORMAT(* *.4F15.8)	0454
000070	GOTO10	C455
		0456
000072	END	0457

REFERENCES

- 1. Gold, Bernard; and Rader, Charles M.: Digital Processing of Signals. McGraw-Hill Book Co., Inc., c.1969.
- 2. Golden, Roger M.: Digital Filter Synthesis by Sampled-Data Transformation. IEEE Trans. Audio & Electroacoust., vol. AU-16, no. 3, Sept. 1968, pp. 321-329.
- 3. Kaiser, J. F.: Digital Filters. System Analysis by Digital Computer, Franklin F. Kuo and James F. Kaiser, eds., John Wiley & Sons, Inc., c.1966, pp. 218-285.
- 4. Rader, Charles M.; and Gold, Bernard: Digital Filter Design Techniques in the Frequency Domain. Proc. IEEE, vol. 55, no. 2, Feb. 1967, pp. 149-171.
- 5. Ferguson, Michael J.; and Mantey, Patrick E.: Automatic Frequency Control Via Digital Filtering. IEEE Trans. Audio & Electroacoust., vol. AU-16, no. 3, Sept. 1968, pp. 392-397.
- 6. Steiglitz, Kenneth: Computer-Aided Design of Recursive Digital Filters. IEEE Trans. Audio & Electroacoust., vol. AU-18, no. 2, June 1970, pp. 123-129.
- 7. Jackson, Leland B.; Kaiser, James F.; and McDonald, Henry S.: An Approach to the Implementation of Digital Filters. IEEE Trans. Audio & Electroacoust., vol. AU-16, no. 3, Sept. 1968, pp. 413-421.




Figure 1.- Signal flow graph of cascaded digital filter.


 $\theta_{\mathbf{k}} = 1 - 2 \Omega_{\mathbf{k}} \quad (0 \le \Omega_{\mathbf{k}} \le 1)$

 $M_k = Unspecified \quad (0 \le \Omega_k \le 1)$

Figure 2.- Two-stage linear-phase filter.


(a) Lag filter.

Figure 3.- Two-stage constant-phase filters.




(b) Lead filter.

Figure 3.- Concluded.




(a) Unspecified phase filter. $\lambda = 0$.

Figure 4.- Two-stage limited-band constant-gain filters.




(b) Linear-phase filter. $\lambda = 10$.

Figure 4.- Continued.




(c) Linear-phase filter. $\lambda = 1000$.

Figure 4.- Concluded.



(a) Unspecified-phase filter. $\lambda = 0$.

Figure 5.- Two-stage low-pass filters.




(b) Zero-phase filter. $\lambda = 10$.

Figure 5.- Continued.

 $(0.0 \le \Omega_{k} < 0.5)$ $(\Omega_{k} = 0.5)$ $(0.5 < \Omega_{k} \le 1.0)$ $(0.0 \le \Omega_{k} \le 0.5)$ (elsewhere) 12.0 E 1.0F .8 .6 Normalized phase, $\Phi_{\mathbf{k}}/\pi$ Magnitude, $A*|H_K|$ -. 8€ ահատու 8 . . 6 Fractional Nyquist frequency, $\Omega_{\mathbf{k}}$ Fractional Nyquist frequency, $\Omega_{\mathbf{k}}$


(c) Zero-phase filter. $\lambda = 1000$.

Figure 5. - Concluded.




(a) Unspecified-phase filter. $\lambda = 0$.

Figure 6.- Three-stage low-pass filters.



(b) Zero-phase filter. $\lambda = 10$.

Figure 6.- Continued.



(c) Zero-phase filter. $\lambda = 1000$.

Figure 6.- Concluded.




Figure 7.- Three-stage low-pass filter.

OFFICIAL BUSINESS
PENALTY FOR PRIVATE USE \$300

FIRST CLASS MAIL





029 001 C1 U 08 720317 S00903DS DEPT OF THE AIR FORCE AF WEAPONS LAB (AFSC) TECH LIBRARY/WLOL/.
ATTN: E LOU BOWMAN, CHIEF KIRTLAND AFB NM 87117

POSTMASTER:

If Undeliverable (Section 158 Postal Manual) Do Not Return

"The aeronautical and space activities of the United States shall be conducted so as to contribute... to the expansion of human knowledge of phenomena in the atmosphere and space. The Administration shall provide for the widest practicable and appropriate dissemination of information concerning its activities and the results thereof."

— NATIONAL AERONAUTICS AND SPACE ACT OF 1958

NASA SCIENTIFIC AND TECHNICAL PUBLICATIONS

TECHNICAL REPORTS: Scientific and technical information considered important, complete, and a lasting contribution to existing knowledge.

TECHNICAL NOTES: Information less broad in scope but nevertheless of importance as a contribution to existing knowledge.

TECHNICAL MEMORANDUMS: Information receiving limited distribution

because of preliminary data, security classification, or other reasons.

CONTRACTOR REPORTS: Scientific and technical information generated under a NASA contract or grant and considered an important contribution to existing knowledge.

TECHNICAL TRANSLATIONS: Information published in a foreign language considered to merit NASA distribution in English.

SPECIAL PUBLICATIONS: Information derived from or of value to NASA activities. Publications include conference proceedings, monographs, data compilations, handbooks, sourcebooks, and special bibliographies.

TECHNOLOGY UTILIZATION
PUBLICATIONS: Information on technology
used by NASA that may be of particular
interest in commercial and other non-aerospace
applications. Publications include Tech Briefs,
Technology Utilization Reports and

Technology Surveys.

Details on the availability of these publications may be obtained from:

SCIENTIFIC AND TECHNICAL INFORMATION OFFICE

NATIONAL AERONAUTICS AND SPACE ADMINISTRATION

Washington, D.C. 20546